11 Series Door Position Switches

IPIXA Security 11 Series Door Position Switches are developed to monitor the open or closed position of the door and send the status back to the control panel. IPIXA door position swtiches are by default connected in closed loop. 11 Series offers a wide variety of aesthetic and functional options in terms of size, shape, color, mounting options & departure gaps to cater to all types of wooden, steel & aluminium doors.

Concealed / Recessed Door Position Switches



Page 1 of 2



AFS1134

IPIXA SECURITY LIMITED Kemp House, 160 City Road, London, EC1V 2NX, United Kingdom ipixa.co.uk

AFS1136

AFS1135

11 Series Door Position Switches

Concealed / Recessed Door Position Switches Specifications

Part #	AFS1130	AFS1131	AFS1132	AFS1133
Diameter	3/8"	3/8"	3/8″	3/8"
Mounting Type	Concealed	Concealed	Concealed	Concealed
Fix Type	Press to Fit	Press to Fit	Press to Fit	Press to Fit
LEADS (Wire)	22 AWG	22 AWG	22 AWG	22 AWG
Color	White	Brown	Grey	White
Departure Gap	20 mm	27 mm	28 mm	22 mm
Switching V & A	100 V DC/AC 0.5 A			

Part #	AFS1134	AFS1135	AFS1136
Diameter	3/4"	3/4"	3/4"
Mounting Type	Concealed	Concealed	Concealed
Fix Type	Self Locking	Self Locking	Press to Fit
LEADS (Wire)	22 AWG	22 AWG	No Cable
Color	White	Brown	Grey
Departure Gap	24 mm	25 mm	17 mm
Rating	100 V DC/AC 0.4 A	100 V DC/AC 0.4 A	100 V DC/AC 0.4 A



Page 2 or 2







IPIXA SECURITY LIMITED Kemp House, 160 City Road, London, EC1V 2NX, United Kingdom ipixa.co.uk